CLAIMS

- 1 1. A humidity control system comprising:
- 2 an inside room humidity sensor;
- a humidity controller having a selectively actuatable humidity level
- 4 selection control for selecting a target in-room humidity;
- 5 an outside temperature sensor circuit; and
- an outside temperature humidity compensator circuit responsively
- 7 coupled to said outside temperature sensor circuit and to said humidity
- 8 controller,
- whereby sensed outside temperature causes said outside temperature
- 10 humidity compensator circuit to automatically adjust the target in-room
- 11 humidity produced by said humidity controller.
 - 1 2. A system as in Claim 1, wherein said outside temperature sensor
- 2 circuit comprises a thermistor circuit.
- 1 3. A system as in Claim 1, wherein said outside temperature humidity
- 2 compensator circuit includes
- a compensation network including said outside temperature sensing
- 4 circuit; and
- 5 an adjustment control circuit.
- 1 4. A system as in Claim 3, wherein said outside temperature humidity
- 2 compensator circuit further includes
- a control switch having a first switch position to select coupling said
- 4 inside room humidity sensor directly to said humidity controller and having

- 5 a second switch position to couple said compensation network and
- 6 adjustment control circuit to said inside room humidity sensor and to said
- 7 humidity controller.
- 1 5. A system as in Claim 3 wherein said compensation network includes:
- an input divider circuit including said outside sensor circuit; and
- a first compensating circuit coupled to said inside room humidity
- 4 sensor and to said input divider circuit to provide a first variable bias signal
- 5 level responsive to outside temperature sensed by said outside temperature
- 6 sensor circuit.
- 1 6. A system as in Claim 5, wherein said adjustment control circuit
- 2 includes
- an output circuit coupled intermediate said inside room humidity
- 4 sensor and said humidity controller, said output circuit also coupled to said
- 5 first compensating circuit, said output circuit to provide an output signal to
- 6 said humidity controller; and
- a selectively variable circuit coupled to said inside room humidity
- 8 sensor, to said outside temperature sensor, and to said output circuit to
- 9 provide a second variable bias signal level,
- whereby said output circuit provides said output signal determined by
- said outside temperature sensed and the setting of said selectively variable
- 12 circuit.
- 1 7. A system as in Claim 5, wherein said outside temperature sensor
- 2 circuit includes

- a thermistor whose resistive value varies with changes in ambient temperature.
- 1 8. A system as in Claim 5, wherein said selectively variable circuit
- 2 includes a first manually adjustable potentiometer.
- 1 9. A system as in Claim 5, wherein said input divider circuit includes a
- 2 second manually adjustable potentiometer to provide controlled calibration
- 3 of said output signal.
- 1 10. A system as in Claim 1, wherein said outside humidity compensator
- 2 circuit comprises:
- a circuit common connection;
- a power input terminal for coupling to a source of power;
- a temperature sensitive resistor having a first connection and a second
- 6 connection coupled to said circuit common connection;
- a first transistor having a first element coupled to said inside humidity
- 8 sensor, a second element coupled to said humidity controller, and a third
- 9 element;
- a load resistor coupled between said second element and said circuit
- 11 common connection;
- a first variable resistor having a wiper element coupled to said third
- 13 element;
- a first resistor coupled intermediate said inside room humidity sensor
- 15 and said first variable resistor;
- a first diode having a first diode terminal and a second terminal, said
- 17 first diode terminal coupled to said first variable resistor;

18	a second resistor coupled intermediate said second diode terminal an	ıd
19	said first connection:	

- a second transistor having a fourth element coupled to said third element, a fifth element, and a sixth element;
- 22 a third resistor coupled intermediate said fifth element and said inside 23 room humidity sensor;
- 24 a fourth resistor coupled intermediate said power input terminal and 25 said sixth element; and
- 26 a fifth resistor coupled intermediate said sixth element and said circuit 27 common connection.
 - 1 11. A system as in Claim 10, and further including
 - a second diode coupled intermediate said second element and said third element.
 - 1 12. A humidity adjusting method comprising:
 - providing selectively reduced signals indicative of sensed indoor
 humidity levels;
 - sensing changes in outside temperature and developing temperature controlled adjusting signals indicative of such changes; and
 - combining the selectively reduced signals and the adjusting signals for providing output signals for use in controlling the operation of a humidity controller.
 - 1 13. The method of Claim 12, and further comprising:
 - developing a source of setpoint settings and rate of humidity change settings for a predetermined range of outside temperatures and a

- 4 predetermined range of percentage of humidity changes associated with
- 5 changes in outside temperature; and
- selecting the setpoint setting and the rate of humidity change setting
- 7 from the source of settings for a desired outside temperature range and a
- 8 desired rate of humidity change.
- 1 14. For use in humidity control system, an outside temperature humidity
- 2 compensating system comprising:
- 3 receiving means for receiving indicators of changes in outside
- 4 temperature;
- 5 humidity receiving means for receiving humidity signals indicative of
- 6 the in-room humidity;
- 7 reducing means for reducing received humidity signals by a selectable
- 8 predetermined amount and for providing reduced humidity signals;
- 9 adjusting means for providing adjusting signals in response to
- 10 received indications of changes in outside temperature; and
- outputting means for providing output signals in response to the
- 12 adjusting signals and the reduced humidity signals,
- whereby the output signals can be utilized to control a humidity
- 14 controller.
 - 1 15. A system as in Claim 14, wherein said reducing means includes:
- 2 rating means for permitting manual selectable settings for defining the
- 3 rate of percentage of humidity change for a range of temperature changes.

- 1 16. A system as in Claim 14, wherein said adjusting means includes:
- voltage dividing means for shifting voltage levels in response to
- 3 sensed changes in the outside temperature; and
- 4 voltage adjusting means for providing the adjusting signals in
- 5 response to changes in the voltage dividing means.
- 1 17. An outside temperature humidity compensation circuit comprising:
- a first input circuit for receiving humidity signals from a humidity
- 3 sensor;
- a second input circuit for coupling to an outside temperature sensor
- 5 circuit;
- a first compensating circuit coupled to said first input circuit and said
- 7 second input circuit to provide a first variable temperature compensating
- 8 signals in response to changes in outside temperature;
- 9 an output circuit; and
- a selectively variable circuit coupled to said first input circuit, to said
- second input circuit, to said first compensating circuit, and to said output
- circuit to provide second variable signals to said output circuit,
- whereby said output circuit provides said second variable signals
- 14 determined by changes in outside temperature and the setting of said
- selectively variable circuit.
- 1 18. The circuit of Claim 17, and further including a thermistor coupled to
- 2 said second input circuit.

- 1 19. A circuit as in Claim 17, wherein said selectively variable circuit
- 2 includes a manually adjustable potentiometer for adjusting the effective rate
- 3 of percentage of humidity change.
- 1 20. The circuit of Claim 17, and further including a control switch
- 2 coupled between said second input circuit and said output circuit,
- whereby the compensation circuit can be switch active or inactive.